



SpinCore TTL Line Driver

Model DRX-4

Owner's Manual



SpinCore Technologies, Inc.
www.spincore.com

Congratulations and *thank you* for choosing a design from SpinCore Technologies, Inc.

We appreciate your business!

At SpinCore we aim to fully support the needs of our customers. If you are in need of assistance, please contact us and we will strive to provide the necessary support.

© 2012 SpinCore Technologies, Inc. All rights reserved.

SpinCore Technologies, Inc. reserves the right to make changes to the product(s) or information herein without notice.

SpinCore TTL Line Driver and the SpinCore Technologies, Inc. logos are trademarks of SpinCore Technologies, Inc. All other trademarks are the property of their respective owners.

SpinCore Technologies, Inc. makes every effort to verify the correct operation of the equipment. This equipment version is not intended for use in a system in which the failure of a SpinCore device will threaten the safety of equipment or person(s).

Table of Contents

<u>I. Introduction.....</u>	<u>4</u>
Product Overview	4
Driver Architecture	4
Design Overview.....	4
Specifications.....	4
<u>II. Connecting to the SpinCore TLL Line Driver.....</u>	<u>5</u>
Connector Information.....	5
Connecting to the Device.....	5
Available Models.....	6
<u>Contact Information.....</u>	<u>6</u>
<u>Document Information.....</u>	<u>6</u>

I. Introduction

Product Overview

The SpinCore TTL Line Driver is a USB powered device equipped with four input channels and 8 output lines. Each of the output lines are capable of producing TTL levels over a 50 Ω load. To allow for a greater range of applications, four of the 8 output lines have been inverted. All input channels and output lines are accessible via BNC connectors. The SpinCore TTL Line Driver is available with a full 2U rack-mount enclosure (model DRX-4E). Another option for the SpinCore TTL Line Driver is a 2U rack-mount front panel only (model DRX-4F). The third and final model is without an enclosure (model DRX-4B).

Driver Architecture

Design Overview

The SpinCore TTL Line Driver utilizes a NAND gate (Philips **74F3037N**) to drive the input signal to TTL level outputs over a 50 Ω load. The drive capability of the Philips 74F3037N allows 67 mA source and 160 mA sink. Typical rise and fall times of the Philips 74F3037N are 2.5 ns, with typical propagation delays of 2.0 ns. *If you require better performance please contact SpinCore for inquiries on pricing.




Figure 1: Above is a schematic of a single channel on the SpinCore TTL Line Driver. An input TTL signal is internally terminated over 200 Ω and driven through two NAND gates to create a non-inverted signal. Additionally, a inverted signal is also created by driving the input signal through one NAND gate.

Specifications

- Four BNC input channels with 200 Ω internal termination. TTL levels required.
- Four BNC non-inverted digital outputs. TTL levels assured over 50 Ω .
- Four BNC inverted digital outputs. TTL levels assured over 50 Ω .
- 67 mA output drive capability for high state.
- 160 mA output drive capability for low state.
- Please refer to this [link](#) for more electrical and timing specifications of the Philips 74F3037N.

II. Connecting to the SpinCore TLL Line Driver

Connector Information

The device has a total of 12 BNC connectors and one USB Type B Connector. Starting from the left edge of the device is the USB connection. The first four BNC connectors next to the USB connection are used as inputs from other TTL devices. The middle four BNC connectors are the inverted output lines, and the last four BNC connectors are the non-inverted output lines. Each of the four input channels has a corresponding inverted and non-inverted output line which can be identified below by the numbers in the figure. **Figure 2** provides a representation of the connector locations.




Figure 2: Connector Locations

Connecting to the Device

The SpinCore TTL Line Driver board is a USB powered device. The device does not require the installation of drivers or for the host computer to be turned off before being plugged in. Simply connect the USB Type B cable to the board and host computer to power on the board.

Connecting the SpinCore TTL Line driver to other devices is very quick and simple. Once the board has been powered on, connect the output of your device to one of the four input BNC connectors of the SpinCore TTL Line Driver using a standard 50 Ω BNC cable.

If using a high-input-impedance oscilloscope to evaluate the performance of the SpinCore TTL Line Driver, place a resistor that matches the characteristic impedance of the transmission line in parallel with the coaxial transmission line at the oscilloscope input. (e.g., a 50 Ω resistor with a 50 Ω transmission line, see **Figures 3** and **4** below). When using an oscilloscope with an adjustable bandwidth, set the bandwidth to as large as possible. These settings are crucial to yield accurate readouts on the oscilloscope.



Figure 3: BNC T-Adapter (left) and 50 Ω BNC resistor (right)



Figure 4: BNC T-Adapter on the oscilloscope with coaxial transmission line connected on the left and BNC 50 Ω resistor connected on the right to terminate the line.

Available Models

The SpinCore TTL Line Driver is available in three models which are listed below. Ordering information can be found at this [link](#).

- **SpinCore TTL Line Driver DRX-4B** – Equipped with four input channels and 8 output lines, the SpinCore TTL Line Driver delivers enough current driving capabilities to work with 50 Ω loads. This model is the bare board version of the SpinCore TTL Line Driver.
- **SpinCore TTL Line Driver DRX-4E** – The SpinCore TTL Line Driver is placed in a standard 2U rack-mount enclosure that protects the board from outside damage. The enclosure is equipped with two metal handles for mobility and stability. This model is equipped with four input channels and 8 output lines.
- **SpinCore TTL Line Driver DRX-4F** – The SpinCore TTL Line Driver is connected to the front panel of a standard 2U rack-mount enclosure. Please note that the entire SpinCore TTL Driver is not fully enclosed in this model. The front panel has two metal handles for mobility and stability.

Contact Information

SpinCore Technologies, Inc.
4631 NW 53rd Avenue, SUITE 103
Gainesville, FL 32653
USA

Telephone (USA): **352-271-7383**
Fax (USA): **352-371-8679**
Website: <http://www.spincore.com>
Web Contact Form: <http://spincore.com/contact.shtml>

Document Information

- Revision history available at SpinCore.